




Cleanroom Management International

We care for your compliance



®

LogTag UTREL30-WiFi

Quick Start Guide

Version A


www.logtagrecorders.com

Quickstart Guide Contents

What's Included	3
Battery Installation	4
Downloading LogTag Analyzer	5
Running the Connection Wizard	7
Connecting to your WiFi Network	10
Configuring your UTREL30-WiFi	13
Installing the Wall Mount	14
Starting your UTREL30-WiFi	15
LogTag Online	16

What's Included


Please check you have the items shown below before continuing with setting up your UTREL30-WiFi.



UTREL30-WiFi




ST10 External Probe
(Not included)




USB Cable



Glycol Buffer
(Not included)



Wall mount
(Not included)



2x AAA Battery
(Not included)


Battery Installation



The USB cable is the main power method to power the UTREL30-WiFi unit permanently via the USB socket.

AAA batteries are another backup power source to ensure your device continues to record in the event of a power outage or is unplugged.

1. You will need a small Phillips (cross-shaped) screwdriver to remove the cover on the back of the UTREL30-WiFi case.



2. Once you have removed the battery cover, install the two AAA batteries. **Take note** of the direction each battery must be installed.
3. Once both batteries are securely installed, **replace the battery cover** and secure via the screw provided.

Downloading LogTag Analyzer

To download the latest LogTag Analyzer, open your browser and navigate to:

 <https://logtagrecorders.com/software/LTA3/>

1. Click 'Go to downloads page' to take you to the download page.
2. Click 'Download Now' to start the download.
3. Click 'Run' or 'Save File' then double-click the downloaded file to open the LogTag Analyzer Setup Wizard.

Warning: Please ensure no other LogTag software is currently running on your computer before running the Analyzer software.

Downloading LogTag Analyzer continued...

4. Follow the on-screen prompts to install LogTag Analyzer.
5. Click 'Finish' to exit the LogTag Analyzer Setup Wizard.

Note: If you already have LogTag Analyzer installed, please see whether you need to update to the latest version by clicking 'Check Internet for updates' from the 'Help' menu.

Running the Connection Wizard

Open LogTag Analyzer and select 'Connection Wizard' from the 'LogTag Online' menu.

Please ensure there is internet connection on your computer prior to starting this process.

The first page of the Wizard will be displayed. When you're ready to begin, click "**Start**".



You will be asked to sign in to your LogTag Online account. If you do not have an account, click the link

Running the Connection Wizard continued...

below or alternatively, open your browser, type the following link into the address bar and follow the on-screen instructions.

<https://logtagonline.com/signup>

or click **Create a LogTag Online Account** link.



The screenshot shows a web browser window titled "LogTag® Online Connection Wizard". The page content includes the following elements:

- Header: "LogTag® Online Connection Wizard"
- Instructions: "Sign in to your LogTag® Online Account below and the Wizard will assist in registering your WiFi device(s). If you do not have an account, click "Create an Account". Return to this Wizard when your account setup is complete."
- Form fields: "EMAIL" and "PASSWORD" with corresponding input boxes.
- Links: "[Forgot your Password?](#)" and "[Create a LogTag® Online Account](#)".
- Footer: "Help Ver: 1.0.8.3" and buttons for "Skip" and "SIGN IN".

Note: If you 'Skip' this step, you will need to manually register the device on LogTag Online or repeat the LogTag Online Connection Wizard.

Click 'Sign In' after you have entered your login details to continue setting up WiFi on your UTREL30-WiFi.


Running the Connection Wizard continued...

You have now created your account and is now ready to set up connection of your UTREL30-WiFi to the WiFi network.



The Wizard will now scan for any connected LogTag devices.

If the scan doesn't find any devices, double-check the device is plugged in to your computer with the USB cable provided and click "Scan Again".



As soon as a device has been identified, it will appear in the table (left) and automatically register that device to your LogTag Online account.

Connecting to your WiFi Network

Serial:	Configured WiFi:	Status:
A0A100003550	LogTag24	Registered

The Status will turn green with the text “Registered” once complete.

If one or more device(s) are identified and registered, the screen automatically switches to the next screen



The screenshot shows a window titled "LogTag® Online Connection Wizard". The window contains the following elements:

- Logo: "LogTag® Online" with a power icon.
- Text: "Please select your Wireless Network from the dropdown below or type it in, provide the password for the chosen network. Then click 'Next'."
- Network Name: A dropdown menu with "LogTag24" selected.
- Network Password: A text input field with "*****" and a toggle icon (eye).
- Advanced Settings: A checkbox labeled "Advanced Settings" which is currently unchecked.
- Footer: "Help Ver: 1.0.8.3" and navigation buttons "< Back" and "Next >".

1. Network settings are automatically populated from PC settings by default, if it can be discovered. Alternatively, click the Network Name arrow to see

nearby Wireless Networks options and select your WiFi Network from the list and type the password for the network. **Remember that passwords are case-sensitive.**

Note: If you need to make any Advanced Network setting changes, select the 'Advanced Settings' box.

2. Once you have provided the chosen network and password, or Advanced Network settings, click **“Next”**.

Note: Some WiFi Networks won't appear in this list for security purposes. If you are aware that your network is one of these, you can manually type the name of your network (SSID) in the Network Name field instead of clicking the menu arrow.



The device is now being configured with the WiFi details you provided in the previous screen, which typically takes 10 seconds.


The Connection Wizard is now checking that the UTREL30-WiFi can connect to your WiFi network and to LogTag Online...



Once the Wizard displays “Connection Succeeded”, click “**Close**” to close the Wizard or click the ‘LogTag Online Sign In page’ link to take you to LogTag Online website.

Configuring your UTREL30-WiFi

Connect your UTREL30-WiFi to your computer via the USB cable provided. The USB socket on the device is located on the bottom, protected by a rubber seal.



1. Open LogTag Analyzer.
2. Click 'Configure' from the 'LogTag' menu or click the 'Wizard' icon.
3. Adjust your logger configuration settings as required.
For more information on configuration settings, please refer to [Configuring the UTREL30-WiFi](#) in the Product User Guide or press 'F1' for help.
4. Click 'Configure' to upload the configuration settings to the logger.
6. Click 'Close' to exit the configuration page.

Installing the Wall Mount

Setup of your UTREL30-WiFi is complete.

Attach the Wall Mount Bracket on the side of your refrigerator or freezer, preferably at eye-level with the adhesive strip provided with the Wall Mount.

Before sticking on the Wall Mount, make sure the sensor cable and the USB cable from the UTREL30-WiFi can both reach the device comfortably without obstruction or at risk of being accidentally disconnected if knocked.

Insert the UTREL30-WiFi into the Wall Mount, connect the USB and sensor cables. The display should show the word “**READY**” as seen in the image (right).

Note: both the cloud and WiFi symbols are showing in the top left with a tick in each to confirm successful setup of the device.



Starting your UTREL30-WiFi


Press and hold the **START/CLEAR/STOP** button.

STARTING will appear along with **READY**.

Release the button once **READY** disappears.
The UTREL30-WiFi now records temperature data.

The Logger will **not** start if:

- You release the button before **READY** disappears.
- You keep holding the button for more than 2 seconds after **READY** disappears.
- The backup battery is critically low and the Logger is not connected to power.



LogTag Online


LogTag Online is a secure online service that stores the data recorded from your logger against your account.

Signing in to your LogTag Online Account

Open your browser and navigate to:
<https://logtagonline.com>

1. Type your Email and Password, then click “Sign In”.

Note: If you did not create an account during the Connection Wizard process, click the ‘Create an Account’ link and follow the on-screen instructions.



The screenshot shows the sign-in page of the LogTag Online service. At the top, there are four welcome messages in different languages: "Bienvenido", "Willkommen", "добро пожаловать", and "欢迎". Below this, there is a central form with the following elements: an "EMAIL" section with a text input field labeled "Email Address"; a "PASSWORD" section with a text input field labeled "Password"; a "Stay signed in" checkbox; a prominent green "SIGN IN" button; a link for "Create an Account" in orange text; and a link for "Forgot your Password?" in red text. At the bottom right of the form, the version number "1.0.5.6330" is displayed.

Upon signing in, you will see the main Dashboard with the Location automatically created.

If you cannot see the Location, manually register the device by clicking the green ‘Register Device’ button in the ‘Recently Registered Devices’ section of the

LogTag Online Team JS Hello JShi

Dashboard 1 / 1 Locations | 0 / 30 File Limit | 1 / 2 Team Members

Pinned Locations (View all)

Last Reading at: **UTRED30-WIFI - A0A1001142ZT** Temperature: ---

⓪ Waiting for first connection... INSPECT

Recently Uploaded Files

Your most recent LogTag Drive files will appear here.

Recently Registered Devices (View all) Register Device

Model	Device Name	Serial Number	Last Connection
UTRED30-WIFI	UTRED30-WIFI	S/N:A0A1001142ZT	06:26 Nov-05-2020

Navigation Bar: Dashboard | Shipments | Locations | Devices | LogTag Drive

main dashboard or select the Devices menu from the bottom navigation bar.

Once the device is registered, the location is automatically created and will appear in Pinned Locations on the Dashboard or in the Locations section in the bottom navigation bar

For more information about registering Devices or Locations, please refer to the 'Devices' or 'Locations' section in the LogTag Online Quick Start Guide.

CMI BELGIUM
 Avenue de Ramelot 3
 B - 1480 Saintes (Sint Renelde)
 Tel : +32 (0)2 531 11 21
 info@cmitest.com

CMI THE NETHERLANDS
 Luchthavenweg 81
 NL - 5657 EA Eindhoven
 Tel : +31 (0)402 88 87 57
 infoNL@cmitest.com

CMI FRANCE
 Ecoparc d'Affaires
 F- 41210 Neung-sur-Beuvron
 Tel : +33 (0)2 54 95 70 95
 infoFR@cmitest.com

Agence Rhône Alpes :
 F- 26160 La Bégude-de-Mazenc
 Tel : +33 (0)4 75 54 57 26



www.cmitest.com